



**Description:** The OS-440 is the industry's first outdoor smart amplifier. The OS-440 can live entirely outside, allowing unprecedented freedom when designing outdoor audio systems. Without being tethered to the house, the OS-440 can wirelessly connect to the home's network, interface with DLNA servers and even allows wireless multi-zone control. On-board Bluetooth functionality and a WiFi direct mode round out the wireless connectivity options.

**Features:**

- 4-channels x 40W or bridgeable into 2 x 80W
- Control source selection from the unit, or from the Mobile App
- Bluetooth and WiFi antennas ensure strong, consistent wireless performance
- Digital and analog source inputs

**Applications:**

Applications for the OS-440 include indoor/outdoor pool areas, patios and courtyards, residential backyards and other indoor or outdoor venues.

**Phase Technology**

8005 W. 110th Street  
Suite 208  
Overland Park, KS 66102  
Phone: 913.663.5600  
Fax: 913.663.3200  
Toll Free: 855.663.5600  
www.phasetech.com

**OS-440 PRODUCT SPECIFICATIONS**

CHANNELS	2/4
POWER PER CHANNEL @<1% THD	80 Watts @ 8 Ω (2 Channel)   40 Watts @ 4 Ω (4 Channel)
EQ	Bass/Treble
BRIDGEABLE	Yes
100V/70V	No
SIGNAL TO NOISE RATIO	82 dB
GAIN	29.5 dB
INPUTS	Optical, Analog Mini, BT, WiFi
INPUT IMPEDANCE	12K Ω
HIGH PASS FILTER (F3)	20 Hz
LOW PASS FILTER	20 kHz
HEIGHT	1.23 in / 31.24 mm
WIDTH	3.98 in / 101.09 mm
DEPTH	4.86 in / 123.44 mm
WEIGHT (AMP & POWER SUPPLY)	3.74 lbs
INCLUDED ACCESSORIES	Outdoor Weatherize Kit
REGULATORY - CE	Approved
REGULATORY - UL	Approved
RoHS	Approved
UNITS PER BOX	1 Unit
OPERATING TEMP RANGE	-20°F - 150°F